



## BOOST

### PMR446 TRANSCEIVER

- 8 PMR446 Channels
- Monitor Function
- Power Save function
- Lower battery alert
- English voice announcement
- Call Function
- Emergency Call
- FMW receiver
- Long operating time with the supplied battery
- PC programmable functions:
  - 50 CTCSS/83 DCS Sub-Audio Tones
  - Scan function
  - VOX function
  - Squelch treshold level
  - TX channel block
  - Voice announcement
  - Key beep.

Supplied with: 7,4V/1800mAh Li-Ion battery pack, battery-charger, beltclip and italian/english user manual.

**Boost** - PMR446 Transceiver

Ref. 7200002

#### Accessori opzionali

PB-6	7,4V/1800mAh Li-Ion battery pack	7205123
CB-6	Desktop Battery charger	7205124
AM-6	Wall charger adapter	7205125
KEP-200EK	Earphone	7205015
MEP-409KL	Air microphone-earphone	7205011
PX-20	Mic-hook type earphone	7205010
PX-22	Speaker-microphone	7205012
X-17K PLUS	Laringophone/earphone	7205077
CP-6	Cloning cable	7205128
CS-02	Nylon Case Big with straps	7205120

#### Technical Specification

Frequency	446,00625 - 446,09375MHz
Channel	8
Modulation	(FM)
Working Temperature	-10°C ~ 55°C
Voltage	7.4V
Standby Current (power Save)	about 25mA (with energy save)
Dimension/Weight	139 (A) × 62(L) × 41(P) / 266g (approx.)
Frequency tolerance	±3ppm
Output Power	≤500mW erp
TX current	≤700mA
Maximum frequency deviation	±2.5
Sensitivity	<-122dB (12dB, S/N)
Squelch Sensitivity	≤-128 dBm
Audio Power	≥500mW
RX current	≤500mA
Audio distortion	<5%
Intermodulation Rejection	≥60dB